

KAPA Energie Solar Ready UPS System

Q2400

1734wH

Pure Sinewave
Inverter



Solar Ready UPS System

Household Use

Q2400



PHONE CHARGER
5W
480 CHARGES*



LED LIGHT
10W
240 HOURS**



WIFI ROUTER
10W
240 HOURS**



LAPTOP CHARGER
50W
48 CHARGE*



TELEVISION
50W
48 HOURS**



REFRIGERATOR
50W
48 HOURS**



COFFEE MACHINE
1400W
1.5 HOURS**



ELECTRIC DRILL
900W
2.5 HOURS**

Capacity



1743WH

Inverter



Pure Sine Wave

SPECIFICATIONS

Rated Capacity	1743wH - (Samsung Lithium Battery)
Inverter	Pure sine wave
Output Port	USB-A (5V 2.4A) x3 TYPE-C (PD 60 W max) x1 AcX3 (2400W output power, 4000W surge Power)
Car Port	N/A
DC Input Port	N/A
Solar Charge	Anderson Power Port (APP),11-82V, 25A max, 1300w MPPT
AC Input Port	1300W
LCD	YES
Size	434 x 314 x 271.5 mm
Weight	24KGS
Standard accessories	AC charging cord+ 1 user manual+ MC4 adapter

CALCULATION

Power Station Wattage ÷ Appliance Wattage = Hours of continuous use

Appliance usage calculations based on single appliance use on power station. Combining appliances will reduce power station usage time.

* Full charge cycles | ** Continuous use